

# TORK®

## WFTU40

# 7-DAY TIME SWITCH

## MULTI-VOLTAGE WI-FI TIMER

### 120/208 – 240/277VAC

DESCRIPTION	FEATURES
<ul style="list-style-type: none"> <li>Commercial grade</li> <li>Indoor/outdoor plastic case</li> <li>UL tested per UL/CSA</li> </ul> 	<ul style="list-style-type: none"> <li>Dual voltage ready</li> <li>DPST Contacts</li> <li>ON/OFF controls</li> <li>ON/OFF override</li> <li>Wi-Fi app ready</li> <li>Surge protected</li> <li>Two year warranty</li> </ul>     



RATINGS	TYPE	VOLTAGE 60Hz	NO	NC
	Resistive		120-277VAC	40A
		28VDC	20A	-
Inductive		120-277VAC	30A	15A
	Ballast	120VAC	30A	10A
277VAC		20A	10A	
Tungsten		120VAC	15A	-
	Pilot Duty	120VAC	720 VA	-
125VAC		-	290 VA	
240VAC		720 VA	360 VA	
Motor	120VAC	1HP 30FLA 90LRA	1/4HP 12FLA 30LRA	
	240VAC	2HP 20FLA 60LRA	-	
	250VAC	-	1/2HP 12FLA 33LRA	




⚠ WARNING: Cancer and reproductive harm. [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov).




### WIRING INSTRUCTIONS & DIAGRAM

Use copper wire AWG 8-18 suitable for 90°C. WIRING TO COMPLY WITH ALL LOCAL AND NATIONAL ELECTRICAL CODES. Bonding between conduit connection is not automatic and must be provided as part of the installation. THE ENCLOSURE MUST BE PROPERLY GROUNDED. Minimum 10.6 lb. in. torque required at the terminals to ensure proper connections. Strip the supply and load wires to 1/2".

Typical Wiring Diagram, 120/277VAC Application



Typical Wiring Diagram, 208-240 VAC Application



Scan with a mobile device for additional information.



FCC Statement: This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation of the device. FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.



50 West Stoever Ave. • Myerstown, PA 17067  
1-800-845-3374 • [www.farmerboyag.com](http://www.farmerboyag.com)